

TITLE OF THE INVENTION

IMAGE PROCESSING METHOD AND APPARATUS

5

FIELD OF THE INVENTION

09678297-100300
This invention relates to an image processing
apparatus and method for converting a multilevel image
to a binary image. More particularly, the invention
10 relates to an image processing apparatus and method
capable of changing dot connectivity when binarization
is performed in dependence upon a parameter.

BACKGROUND OF THE INVENTION

15

Many methods of binarizing multilevel image data in
order to output the data to a binary (bi-level) printer
such as an ink-jet printer have been proposed. One
binarization processing technique known in the art is
20 the error diffusion method, which is a method of
reproducing pseudo-halftones.

As disclosed in R.W. Floyd and L. Steinberg,
"Adaptive algorithm for spatial grey scale", SID Int.
Sym. Digest of Tech. Papers, p. 36-37 (1975), the error
25 diffusion method binarizes (converts to a maximum
density level or maximum contrast level) multilevel

image data of a pixel of interest, weights the error between the binarized level and the multilevel data that prevailed prior to binarization and adds the weighted error to the data of pixels neighboring the pixel of interest.

5 An example of a generally known apparatus which uses such a binarization method is a copier having a plurality of printing elements which print in accordance with thermal transfer or ink-jet technology. Another
10 example is an electrophotographic copier which uses light-emitting elements such as LEDs.

Such copiers have a reading unit equipped with an optoelectric transducer such as a CCD and convert a document image to an electric signal by causing the
15 reading unit to scan the document. Printing is performed by driving a plurality of printing elements on a printhead based upon the electric signal obtained by scanning, and the document image is reproduced on a printing medium such as printing paper by a well-known
20 electrophotographic process or ink-jet technique.

A copier/MFP (multifunction printer) in which an image read by a reader can be printed directly by another printer via a network has been proposed in recent years.

25 Fig. 21 is a diagram illustrating the configuration of a network-connected image processing system.

As shown in Fig. 21, the system includes MFPs 2101, 2104 in which an image that has been read by a self-contained reader is printed out directly by each printer, a backbone network 2102, a computer 2103, a copier 2105 having a printing function and a printer 2016.

The computer 2103 is located in an environment in which each printer or the copier is capable of printing out images via the network 2102. Further, the MFP 2101 is capable of outputting an image read by its self-contained reader to the other printers or to the copier directly via the network 2101 without the intermediary of the computer 2103. Such output is possible irrespective of whether models are of the same type, such as the MFP 2104.

In such cases it is desirable for a read image to be transmitted upon being binarized in order to reduce the load on the network 2102. Accordingly, there are many cases in which use is made of error-diffusion-type 20 binarization, which exhibits excellent tone reproduction and resolution.

Often, however, the reproducibility of isolated dots in electrophotography or the like is dependent upon the print engine. There are instances where an image
25 having very poor tone reproduction is output, depending

upon the printer, owing to variations in isolated-dot reproduction from one engine to another.

Further, the reproducibility of isolated dots depends greatly upon the process conditions, and dot reproducibility varies markedly owing changes in process conditions brought about by changes in the environment or change with time.

With error-diffusion-type binarization, there is a high likelihood that dots will be printed in isolated form and hence the effects brought about by discrepancies in the reproducibility of isolated dots is great.

SUMMARY OF THE INVENTION

15 Accordingly, an object of the present invention is
to provide an image processing apparatus and method in
which the connectivity of a binary image is controlled
to deal with a change in binary-image reproducibility
20 caused by differences in the characteristics of image
output devices on a network and by changes in the
environment and change with time, thereby making it
possible to optimize connectivity, achieve stable
reproduction and improve image quality.

25 According to the present invention, the foregoing
object is attained by providing an image processing

apparatus having input means for inputting, pixel by pixel, a multilevel image containing gray-scale information, and binarization means for binarizing the multilevel image, which has been input by the input
5 means, to a binary image, the apparatus comprising:
communication means for communicating with an external image output device via a network; characteristic-information storage means for receiving characteristic information of the external image output device from the
10 communication means and storing the characteristic information; connectivity control means for controlling connectivity of a binary image, which is binarized by the binarization means, based upon the characteristic information stored by the characteristic-information
15 storage means; and transmitting means for transmitting the binary image, the connectivity of which has been controlled by the connectivity control means, to the external image output device via the communication means.

20 Further, according to the present invention, the foregoing object is attained by providing an image processing apparatus having input means for inputting, pixel by pixel, a multilevel image containing gray-scale information, and binarization means for binarizing the
25 multilevel image, which has been input by the input means, to a binary image, the apparatus comprising:

communication means for communicating with an external image output device via a network; characteristic-information storage means for storing characteristic information of the external image output device;

- 5 connectivity control means for controlling connectivity of a binary image, which is binarized by the binarization means, based upon the characteristic information stored by the characteristic-information storage means; and transmitting means for transmitting
- 10 the binary image, the connectivity of which has been controlled by the connectivity control means, to the external image output device via the communication means.

- Further, according to the present invention, the
- 15 foregoing object is attained by providing an image processing apparatus having input means for inputting, pixel by pixel, a multilevel image containing gray-scale information, and binarization means for binarizing the multilevel image, which has been input by the input
- 20 means, to a binary image, the apparatus comprising: communication means for communicating a parameter with an external image output device via a network, the parameter controlling connectivity of a binary image binarized by the binarization means; connectivity
- 25 control means for controlling connectivity of a binary image, which is binarized by the binarization means,

based upon a parameter of an output destination obtained
by the communication means; and transmitting means for
transmitting the binary image, the connectivity of which
has been controlled by the connectivity control means,
5 to the external image output device via the
communication means.

Further, according to the present invention, the
foregoing object is attained by providing an image
processing apparatus having input means for inputting,
10 pixel by pixel, a multilevel image containing gray-scale
information, and binarization means for binarizing the
multilevel image, which has been input by the input
means, to a binary image, the apparatus comprising:
communication means for communicating with an external
15 image output device via a network; reading means for
reading a test pattern for detecting connectivity;
parameter calculation means for calculating a parameter,
which controls connectivity of a binary image binarized
by the binarization means, in conformity with results
20 obtained from the reading means; connectivity control
means for controlling connectivity of a binary image,
which is binarized by the binarization means, based upon
the parameter calculated by the parameter calculation
means; and transmitting means for transmitting the
25 binary image, the connectivity of which has been
controlled by the connectivity control means, to the

external image output device via the communication means.

Other features and advantages of the present invention will be apparent from the following description taken in conjunction with the accompanying drawings, in which like reference characters designate the same or similar parts throughout the figures thereof.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention.

Fig. 1 is a diagram showing the structure of a printing apparatus capable of copying an image in accordance with a first embodiment of the invention;

Fig. 2 is a block diagram illustrating the construction of an image processing section according to the first embodiment;

Fig. 3 is a block diagram illustrating the details of construction of a binarization circuit;

Fig. 4 is a diagram illustrating, in terms of C programming language, processing for calculating a hysteresis control quantity;

Fig. 5 is a block diagram illustrating the details
5 of construction of an error correction unit;

Fig. 6 is a diagram illustrating the details of construction of an error compression circuit and error restoration circuit;

Fig. 7 is a diagram illustrating timing at which a
10 line buffer is accessed;

Fig. 8 is a conceptual view illustrating processing for writing data to the line buffer;

Fig. 9 is a diagram useful in describing addition processing performed by the error correction unit;

15 Fig. 10 is a block diagram illustrating the details
of construction of a binarizer;

Fig. 11 is a block diagram illustrating the details of construction of a binarized-result delay unit;

Fig. 12 is a diagram showing the output state of
20 binarization results Nmn of a plurality of lines;

Fig. 13 is a block diagram illustrating the details of construction of an average-density calculation unit;

Fig. 14 is a diagram illustrating an example of coefficients when processing for calculating average density is executed;

Fig. 15 is a diagram illustrating, in terms of C programming language, processing for calculating a threshold value;

Fig. 16 is a diagram illustrating an array
5 (pattern) of results of binarization;

Fig. 17 is a diagram illustrating, in terms of C programming language, an arithmetic operation performed by an adder;

Fig. 18 is a block diagram illustrating the
10 construction of a random-number generator;

Fig. 19 is a diagram illustrating, in terms of C programming language, the generation of random numbers by the random-number generator;

Fig. 20 is a diagram illustrating, in terms of C
15 programming language, control of amount of addition
performed by an addition-quantity controller;

Fig. 21 is a diagram illustrating a network-connected image processing system;

Fig. 22 is a block diagram illustrating the
20 construction of an image processing section according to
a second embodiment of the present invention;

Fig. 23 is a block diagram illustrating the construction of an image processing section according to a third embodiment of the present invention; and

Fig. 24 is a block diagram illustrating the construction of an image processing section according to a fourth embodiment of the present invention.

5 DESCRIPTION OF THE PREFERRED EMBODIMENTS

Embodiments of the present invention will now be described in detail with reference to the drawings.

[First Embodiment]

10 Fig. 1 is a diagram showing the structure of a printing apparatus capable of copying an image in accordance with a first embodiment of the invention.

As shown in Fig. 1, A document reader 150 includes a document glass 152 on which a document is placed. The document is illuminated by light from an illuminating lamp 156 and light diffused by a diffuser 154, light reflected from the document is reflected by mirrors 155, 158, 159 and passes through a lens 160 so that an image is formed on a CCD 161. The latter converts the light image to an electric signal to obtain an image signal.

The CCD 161 in this embodiment has 7200 pixels arrayed from front to back and is composed of three rows of pixels, namely R (red), green (G) and blue (B) rows.

A reading unit 153 on which the mirror 155 and lamp 156 are mounted moves to the left and right on rails (not shown), and a mirror unit 157 mounting the mirrors

158, 159 moves in sync with the reading unit 153. These two units are capable of reading a document in its entirety by being moved left and right.

A document cover 151 presses the document against
5 the document glass 152.

The image signal read by the document reader 150 is subjected to image processing (described in detail later) and then sent to a printer 100. The latter has a pick-up roller 102 which pulls a sheet of paper from a cassette 101 containing paper as the printing medium. The sheet of paper passes through first registration rollers 103, guide plates 104 and second registration rollers 105 and is attracted to a conveyance belt 106.

Meanwhile, the image signal is divided into the
15 four colors C, M, Y, K. The C (cyan) signal is changed
to a light signal by an LED array 112a and is recorded
on a drum 114a as a latent image. The latent image on
the drum 114a is developed by a developing unit 113a to
form a toner image on the drum 114a. The developed
20 toner image is transferred to the paper on a platen 107.

The above-described process is the well-known electrophotographic process. The remaining colors M (magenta), Y (yellow) and K (black) are similarly subjected to this electrophotographic process by the LED array, drum and developing units, whereby the color images are transferred to the paper.

The toner that has been transferred to the paper is fixed to the paper by a fixing unit 108. Following the completion of toner fixation, the paper is ejected into a drop tray 111 via paper ejection rollers 110.

Fig. 2 is a block diagram illustrating the construction of an image processing section according to the first embodiment

As shown in Fig. 2, the image processing section includes an input sensor 201, which comprises an optoelectric transducer such as a CCD and a driving device for driving the transducer, for reading and scanning a document. An input correction circuit 202 sequentially inputs image data representing the document read by the input sensor 201, quantizes each pixel of the image data to digital data and executes digital processing to perform a shading correction or the like for correcting sensitivity unevenness of the CCD sensor and illumination unevenness caused by the illuminating light source.

20 A digital filter circuit 203 subjects the input
image data to edge emphasis and smoothing. A LOG
conversion circuit 204 converts RGB image data to CMY
data by a look-up table, not shown. A color conversion
processing circuit 205 uses a multidimensional mapping
25 table (not shown) to execute color conversion processing
that corresponds to the colorization characteristic of

the printing toner (or ink).

A gamma conversion circuit 206 uses a one-dimensional look-up table (not shown) to apply a correction so as to linearize tone in dependence upon the printing tone characteristic of the printer. A binarization circuit 207 quantizes multilevel image data to binary data. A selector 208 selects whether to print out the binarized image data or to transmit it to a network. A printhead 209 is controlled to turn dots on or off, thereby to reproduce the image, based upon binary data sent from the binarization circuit 207 by the selector 208.

A CPU 210 identifies a printer with which this system is communicating via the network and selects or
15 calculates connectivity parameters that are optimum for this printer. The CPU 210 controls the overall apparatus in accordance with a program and control data stored in a ROM, not shown. A RAM 211 backs up the connectivity parameters.

20 A network interface 212 serving as network
communication means communicates with another printer
and sends print data via a network. A correlation table
213 stores the correlation between the print
characteristics of each of the printers and connectivity
25 parameters.

In a case where a connectivity parameter is set in

the arrangement described above, first the network interface 212 communicates with the printer where printing is to be performed. Information representing the engine of this printer is sent to the CPU 210. The
5 engine information is information indicating whether the printer at the communication destination has a print engine which operates in accordance with the ink-jet technique, an electrophotographic technique using LEDs or an electrophotographic technique using a laser.

10 A connectivity parameter that is optimum for the printer is calculated by the CPU 210 from the engine information that has been sent. The relationship between engine information and connectivity parameter is found in advance by experimentation, and the correlation
15 is put into table form and stored in the correlation table 213. For example, since an electrophotographic printer using an LED or laser has an isolated-dot reproducibility inferior to that of an ink-jet printer, the parameter is set so as to strengthen connectivity in
20 areas where density is low.

The connectivity parameter is calculated from the relations in the correlation table 213. In a case where there are several connectivity parameters, these may be divided into groups. Further, the parameters may be
25 calculated by a circuit using membership functions or the like. A calculated connectivity parameter is stored

in the RAM 211. When printing is actually performed, the binarization circuit 207 binarizes the image signal using the parameter in the back-up RAM 211.

The details of the binarization circuit 207 will
5 now be described.

Fig. 3 is a block diagram illustrating the details of construction of the binarization circuit 207. The overall flow of signals will be explained before describing the blocks of the binarization circuit and the connectivity parameter in detail.

The binarization circuit 207 includes an error correction unit 302 the inputs to which are error data E, which has been generated by a binarizer 301, and a signal DR' obtained by adding a random number (described later) to an input multilevel signal D from the gamma conversion circuit 206 and dividing the sum by a constant 17.

The error correction unit 302 subjects the entered error data E to an error correction in n-pixel units and outputs the result to the binarizer 301 as an image signal DE.

The inputs to the binarizer 301 are the image signal DE, a binarization slice value S, described later, and a calculated value m of average density, described later. The binarizer 301 compares the image signal DE and the binarization slice value S to obtain a

binary output N. The binarizer 301 then subtracts the calculated value m of average density from the image signal DE to calculate binarization error data E.

A binarized-result delay unit 303 receives the
5 binary output N as an input, applies a delay of a
prescribed number of lines and sends the resulting data
to an average-density calculation unit 304 and
threshold-value calculation unit 305 as binarization
results N_{mn} and B_{ij} of a plurality of lines.

10 The average-density calculation unit 304 receives
the binarization results Nmn of a plurality of lines as
an input, applies a multiply-and-accumulate operation to
coefficients that have been set in advance and to the
delayed binarized result and outputs the calculated
15 value m of average density to an adder 306 and binarizer
301.

The output B_{ij} from the binarized-result delay unit 303, the input multilevel data D and an output T from a hysteresis control quantity calculation unit 308 are input to the threshold-value calculation unit 305. The latter calculates a threshold-value control quantity for any density area in conformity with the B_{ij} signal, which indicates a past binarization condition (pattern), and sends the calculated value to the adder 306 as a binarization slice value S' .

The signals from the average-density calculation

unit 304 and threshold-value calculation unit 305 are
input to the adder 306, which adds these signals and
outputs the sum to the binarizer 301 as the binarization
slice value S. An adder 307 adds the input image signal
5 D and a signal P1 from an addition-quantity controller
313, described later, and outputs the sum DR.

Using the signal DR from the adder 307, the
hysteresis control quantity calculation unit 308
according to this invention calculates a hysteresis
10 control quantity based upon a technique described later
and outputs the control quantity to the threshold-value
calculation unit 305. The hysteresis control quantity
is controlled by referring to values in the back-up RAM
211 which stores the connectivity parameters.

15 A divider 309 divides the input signal DR by the
constant 17 and outputs only the product DR'. Any
remainder is discarded in its entirety. A random-number
generator 310 generates an m-series random number R of
-17 to 7 through a technique described later and outputs
20 the random number R to a selector 312 and to a sign-
reversal and data storage unit 311.

The sign-reversal and data storage unit 311
reverses the sign of the random number R, retains the
data for only a fixed number of pixels, described later,
25 and then outputs the retained random number to the
selector 312. The latter produces an output by

switching between the signal from the random-number generator 310 and the signal from the sign-reversal and data storage unit 311 in response to a pixel position signal having a timing described later.

- 5 In accordance with the value of the image signal D, the addition-quantity controller 313 controls the amplitude of the random-number output value using a technique described later.

 Binarization processing is executed by the
10 binarization circuit 207 constructed as set forth above.

 The details of each component shown in Fig. 3 will now be described.

 First the hysteresis control quantity calculation unit 308 of this invention will be described with
15 reference to Fig. 4.

 The hysteresis control quantity calculation unit 308 varies the value of a constant ALF (= 32) in accordance with the input signal DR and outputs the hysteresis control signal T. The arrangement is such
20 that a change in the hysteresis control signal T causes a change in binarization connectivity.

 The constant ALF is the above-mentioned connectivity parameter and is implemented by a register retained in the back-up RAM 211. Similarly, ALFm is a
25 register held in the back-up RAM 211. If the value of constant ALF is enlarged, dot connectivity in

approaches "0" from the constant ALF (= 32) from "0" as the value of the input signal DR increases from the constant LR3 to the constant LR4.

In a case where the input signal DR is greater than
5 LR4, processing for setting ll to "0" is executed.

After the above-described processing is executed, the result of subtracting the constant ALFm (= 16) from ll is delivered as the output signal T. The purpose of this subtraction operation is to change the signal T of
10 the hysteresis control quantity calculation unit 308 from a negative to a positive value. This makes possible texture control in any density area over a range of broad latitude.

The error correction unit 302 will be described
15 next. The error correction unit 302 adds the binarization error data E to the image signal DR' to calculate the image signal DE that has undergone the error correction, then outputs the signal DE to the binarizer 301. The error correction unit 302 has the
20 construction shown in Fig. 5.

The entered binarization error data E is limited to -6 to +6 by limiter processing (not shown) so as not to be influenced by past binarization results, which is referred to as a dot blanking phenomenon as described in
25 U.S. Patent No. 5,325,448, in a case where the input multilevel data D changes suddenly from high to low

density. The binarization error data E limited to -6 to +6 is halved by a divider circuit 501. The result is branched in two directions so as to enter a subtraction circuit 502 and an error compression circuit 506.

5 The subtraction circuit 502 calculates the
difference $EB (= E - E/2)$ between the binarization error
data E and $E/2$ and outputs this difference to an adder
504. The error compression circuit 506 adds
quantization error in two-pixel units and outputs the
10 sum to a line buffer 503. Fig. 6 is a diagram
illustrating the details of construction of the error
compression circuit 506 and an error restoration circuit
507.

The error compression circuit 506 shown in Fig. 6 includes an adder 602 for adding the entered $E/2$ and data delayed one pixel by a flip-flop 601 and writes the resulting data to the line buffer 503 at a timing $WRclk$ shown in Fig. 7.

More specifically, the error compression circuit
20 506 adds quantization error, which has entered at a
timing 0, 1, 2, 3, 4, 5, ... in terms of pixel position,
in sets of "0, 1", "2, 3", "4, 5", ... and writes the
results to memory at the timing 1, 3, 5, This is
illustrated conceptually in Fig. 8. By using a memory,
25 in which one pixel is represented by two bits (± 1), two
pixels at a time, it is possible to store an error

(data) of up to four bits (± 7).

Storing quantization-error vales in two-pixel units
is advantageous in that it broadens the latitude of the
timing at which the memory is accessed and makes it
5 possible to reduce memory capacity.

The quantization-error value of the preceding line is read out of the line buffer 503 at the timing RDclk shown in Fig. 7 and is input to the error-restoration circuit 507.

10 The error compression circuit 506 sums the
quantization-error value in two-pixel units and stores
the result in the line buffer 503. When the result is
read out of the line buffer 503, therefore, the error-
restoration circuit 507 halves the result using the
15 divider circuit 603, as shown in Fig. 6. The
quantization-error value read out of the line buffer 503
used in correcting the error of each pixel is the same
as that in terms of two-pixel units. However, the
necessary capacity of the line buffer 503 can be reduced
20 with almost no decline in image quality resulting from
this arrangement.

With reference again to Fig. 5, the adder circuit 504 calculates the sum of the output EA from the error-restoration circuit 507 and the output EM from the subtraction circuit 502 and outputs the sum to an adder circuit 505. The latter calculates the sum of EA and EB

delayed by one line and the image signal DR' and delivers the sum as image signal DE.

As shown in Fig. 9, the error correction unit 302 adds the value of binarization error EA obtained when "A" on the overlying line is binarized and the value of binarization error EB when "B" of the preceding pixel is binarized to the data of a pixel of interest indicated by "*", as illustrated in Fig. 9.

Next, the binarizer 301, which receives the image signal DE, the binarization slice value S (described later) and the calculated value m of average density (described later) as inputs and compares these to deliver the binary output N and the binarization error data E. The binarizer 301 is illustrated in Fig. 10.

The input image signal DE enters a comparator circuit 1001 and a subtractor circuit 1002. The comparator circuit 1001 compares the value of the image signal DE and the value of the binarization slice value S and delivers the binary output N in the following manner:

$N = 1$ when $DE > S$ holds; and

$N = 0$ when $DE \leq S$ holds.

The subtractor circuit 1002 subtracts the calculated value m of average density from the value of image signal DE and outputs the difference

$$E = DE - m$$

as the binarization error data E.

At this time limiter processing (not illustrates) is executed in such a manner that the value of E will fall within the range "-6 ~ +6", as mentioned above.

5 The binarized-result delay unit 303, which receives
the binary output N from the binarizer 301 as an input,
applies a delay of a predetermined number of lines and
sends data to the average-density calculation unit 304
and threshold-value calculation unit 305 as the
10 binarization results N_{mn} , B_{ij} of a plurality of lines.
The construction of the binarized-result delay unit 303
is illustrated in Fig. 11.

The applied binary output N is sent from a one-bit, one-line line buffer 1101 to a line buffer 1102 so that the data is delayed line by line. At the same time, the binary output N is successively delayed one pixel by delay elements 1103 to 1108 each comprising a one-pixel delay circuit. The output of delay element 1106 and the output of delay element 1107 are delivered as outputs N14 and N15, respectively.

The binarized data delayed one line by the line buffer 1101 is delayed by delay elements 1109 to 1114 and the outputs of delay elements 1109 to 1113 are delivered as outputs N21 to N25, respectively. The

25 binarized data delayed one line by the line buffer 1102 is delayed by delay elements 1115 to 1120 and the

outputs of delay elements 1115 to 1119 are delivered as outputs N31 to N35, respectively.

At the same time, the outputs of delay elements 1106 to 1108 are delivered as outputs B10, B20, B30, respectively. The binarized data delayed one line by the line buffer 1101 is delivered as outputs B32 to B02 and Bi12 to Bi32 after being delayed. The binarized data delayed one line by the line buffer 1102 is delivered as outputs B31 to B01 and Bi11 to Bi31 after being delayed.

In other words, data obtained by binarizing a two-dimensional image is delayed a plurality of lines and a plurality of pixels and is input to the average-density calculation unit 304 as the binarization results N_{mn} of a plurality of lines in the manner shown in Fig. 12.

The binarization results N_{mn} of a plurality of lines are input to the average-density calculation unit 304, which performs a multiply-and-accumulate operation based upon coefficients that have been set in advance and the delayed results of binarization and outputs the data m used by the binarizer 301 and adder 306. The construction of the average-density calculation unit 304 is shown in Fig. 13.

A multiplier circuit 1301 receives the binarized data N15 and a coefficient M15 as inputs, multiplies these and outputs the product. A multiplier circuit

000001" 46284960

1302 receives the binarized data N14 and a coefficient M14 as inputs, multiplies these and outputs the product. The above operation is performed in similar fashion by multiplier circuits 1303 to 1312. The products obtained
5 by these multiplication operations are summed by an adder circuit 1313. The sum is output as the calculated value m of average density. Fig. 14 is a diagram illustrating an example of coefficients when processing for calculating average density is executed.

10 The threshold-value calculation unit 305 will be described next. Fig. 15 is a diagram illustrating, in terms of C programming language, processing for calculating a threshold value.

First the threshold-value calculation unit 305
15 divides the value of the applied signal T from the hysteresis control quantity calculation unit 308 by each of constants LT1 (= 2) and LT2 (= 4) to obtain variables A (= $T/LT1$), B (= $T/LT2$) used internally.

Next, through a method described below, the
20 threshold-value calculation unit 305 controls the value of the binarization slice value S' by the variables A, B and constants in dependence upon the array (pattern) of results of binarizing the output B'*ij from the binarized-result delay unit 303.

25 Fig. 16 is a diagram illustrating an array (pattern) of results of binarization.

000001 1622950

In this example, reference is not made to the pixel immediately preceding the pixel of interest in order to achieve high-speed processing. Of course, if sufficiently fast logic is incorporated, the pixel immediately preceding the pixel of interest may be referred to without problems.

Described next will be processing for actually controlling the binarization slice value S in dependence upon the array (pattern) of results of binarization.

10 In a case where binarization conditions surrounding a pixel of interest are as set forth below, the binarization slice value S is output upon being set forcibly to the maximum constant 15. The purpose is to make it difficult to print a dot.

15 B32==0&&B22==1&&B12==0&&B21==0&&B11==1&&B01==0 or
Bi12==0&&Bi22==1&&Bi32==0&&B01==0&&Bi11==1&&Bi21==0

In a case where binarization conditions surrounding a pixel of interest are as set forth below and, moreover, input multilevel data D is less than 31 (31 in 0 to 255), the binarization slice value S is output upon being set forcibly to the maximum constant 15. The purpose is to make it difficult to print a dot when the above-mentioned conditions hold.

25 B12==0&&B02==0&&Bi12==0&&Bi22==0&&Bi32==0&&
B11==0&&B01==0&&Bi11==1&&Bi21==0&&Bi31==0&&B20==0
On the other hand, in a case where the input

multilevel data D is equal to or greater than 31 (31 in 0 to 255) under the above-described conditions, the binarization slice value S is output upon being set to an average-density value of zero. This is to assure that texture control will not be carried out in a case where the past results of binarization have a specific array (pattern). Of course, the constant 31 need not be a decided value and can be a parameter that is set another value such as 48 or 64.

10 If the value is made larger than 31, texture control tends to be applied more easily. Conversely, if the value is made smaller than 31, it goes without saying that texture control becomes less likely to be applied.

15 In a case where binarization conditions surrounding
a pixel of interest are as set forth below, the
binarization slice value S is output upon being set to
-A.

```
B02==0&&B12==0&&B11==0&&B01==1&&B11==1&&B121==0&&
```

20 B20==0

Here the purpose is to make it easier to print a dot when the above-described conditions hold.

Processing is executed without referring to results of binarizing the pixel immediately preceding the pixel of interest.

Similarly, the binarization slice value S' is

performed by the divider 309 (described later) is 17, the remainder after division will be the maximum 16. It is therefore necessary to make the amplitude of the random number an even number of 16 or greater. Hence the constant 8 is found from the operation $16/2$. This added as a bias component.

Though not illustrated, a limiter is applied so that the sum will fall within the range of 0 to 255. The signal from the adder 307 is input to the divider 10 309 and hysteresis control quantity calculation unit 308.

As mentioned earlier, the divider 309 divides by the constant 17. The output value at this time is only the quotient obtained by division; the remainder is discarded in its entirety. The output signal DR' from the divider 309 is input to the error correction unit 302, which proceeds to execute error correction processing.

The random-number generator 310, which is a
processor for generating the random number R, will now
be described. Fig. 18 is a block diagram illustrating
the construction of a random-number generator 310 and
Fig. 19 illustrates random-number generation written in
C programming language.

```

25      First, initialization is carried out to write "0"
      to a register p[ii]: ( $0 \leq ii \leq 25$ ) and to set only a

```

register P[12] to "1". Before a random number is output, the operation $p[0] = ((p[25] \wedge p[24] \wedge p[23] \wedge p[22]) \& 1)$ is performed. Random-number vales -17 to 17 are then generated in accordance with the following operation:

```
5      random number = (1-2*p[22])*((p[15]*64+p[16]*32
      +p[17]*16+p[18]*8+p[19]*4+p[20]*2+p[21])*17)/128)
```

What is important here is that it is necessary to make the maximum value (17 in this embodiment) of the generated random number one-half or more (fractions
10 being discarded) of the divisor (17 in this embodiment) used in the divider 309.

According to this embodiment, the division used in the divider 309 is 17 and, hence we have $17/2 = 8$ (discarding fractions) and it is necessary that the maximum random number generated by the random-number generator 310 be set to a value of 8 or higher (the value is set to 17 in this embodiment).

The random-number generation described above is applied to all pixels.

20 The sign-reversal and data storage unit 311
reverses only the sign of the random-number value from
the random-number generator 310 generated at pixel
positions " $p \times X$ " ($p \geq 2$, where p is an even number, and X
is an address value in the main-scan direction), holds
25 the result for " $p/2$ " pixels and then outputs the result.

For example, if the value of p is "2", random-number values generated at pixel positions " $p \times X$ ", namely at pixel positions "0, 2, 4, 6, 8, 10, 12, 14, ...", are held temporarily and the signs of random-number values that were held at pixel positions "1, 3, 5, 7, 9, 11, 13, 15, ..." are reversed, after which the values are output.

In this embodiment, refresh is performed one pixel at a time.

10 The selector 312 switches between delivering the random-number value from the random-number generator 310 generated pixel by pixel and the random-number value from the sign-reversal and data storage unit 311 in accordance with the pixel-position signal.

15 The pixel-position signal selects the random-number
value from the sign-reversal and data storage unit 311
only when the pixel position is " $p \times X + p/2$ " ($p \geq 2$,
where p is an even number, and X is an address value in
the main-scan direction). At all other times the pixel-
20 position signal selects the random-number value from the
random-number generator 310.

In a case where the maximum random-number value in the random-number generator 310 is greater than one-half (8 after decimals are discarded) of the divisor (17 in this embodiment) used in the divider 309, the addition-

quantity controller 313 applies output control conforming to the input multilevel data D only with respect to this large (superfluous) random number.

Fig. 20 is a diagram illustrating control of amount of addition performed by the addition-quantity controller 313 in C programming language.

A constant SL is decided in such a manner that the maximum value of the output RD from the selector 312 will be one-half the divisor of the divider 309. More specifically, in this embodiment, the maximum value of RD is 17 and the divisor used in the divider 309 also is 17. Accordingly, we have $(\text{maximum value of RD})/2 = 17/2 = 8$ (discarding fractions), and the value of SL is set to 8.

In a case where the input multilevel signal D is equal to or less than N1 (e.g., 16), the minimum necessary random number is added in accordance with the calculation " $P1 = RD/SL$ ".

The minimum necessary random number referred to here means that the deviation in the random number is made "-8 to 8" because the divisor in the divider 309 is "17".

In other words, letting α (= 16) represent the deviation in the random number, the divisor used in the divider 309 satisfies the relation $|\alpha+1|$ (= 17).

dot-connectivity parameters of a binarization circuit can be changed and the connectivity parameters are corrected to optimum values for dealing with variations in dot reproducibility ascribable to differences in engine characteristics from one printer to another. This makes it possible to achieve stable reproduction of dots even in the case of printers connected via network. The end result is improved printing quality.

[Second Embodiment]

10 A second embodiment of the present invention will
now be described with reference to the drawings.

Fig. 22 is a block diagram illustrating the construction of an image processing section according to a second embodiment of the present invention. As shown in Fig. 22, this embodiment differs from the first embodiment of Fig. 2 in that the correlation table 213 of the first embodiment is replaced by a floppy-disk drive 214 and hard disk 215. According to this arrangement, characteristic information concerning each printer can be obtained from a medium such as a floppy disk rather than being stored in advance as in the first embodiment.

With this arrangement, information similar to a PPD file that notifies this apparatus of the characteristics of each printer is provided via a medium such as a floppy disk. The floppy-disk drive 214 reads this

information and stored in on the hard disk 215 via the
CU 210.

In accordance with the second embodiment, data that
has been stored on the hard disk 215 performs a function
5 the same as that of the correlation table.

[Third Embodiment]

A third embodiment of the present invention will
now be described with reference to the drawings.

The third embodiment uses a reader to read a change
10 in dot reproducibility caused by a change in environment
or a change with time of each printer on a network over
which binary data is exchanged, and corrects dot-
connectivity parameters in binarization in order to deal
with dot connectivity that has changed, thereby
15 optimizing dot connectivity to make possible stable
reproduction of dots and provide a network printer
environment in which high-quality printing is obtained
at low cost.

Examples of a change in environment are a change in
20 temperature and humidity brought about a change of
location at which the device is installed. An example
of a change with time is a change in the film thickness
of a drum that accompanies an increase in number of
copies printed.

25 Fig. 23 is a block diagram illustrating the
construction of an image processing section according to

the third embodiment of the present invention.

5 again.

This arrangement will be described in regard to a case where connectivity parameters of the printing apparatus itself are calculated when connectivity parameters are set.

pattern signal. This signal is input as an image signal by the selector 221 and enters the printhead 209, which proceeds to perform printing based upon this binary pattern data. When printing of the test-pattern signal
5 ends, the paper ejected from the printer is placed upon the document glass 152 and is read in. Data that has entered from the input sensor 201 passes through the input correction circuit 202 and filter 203 (unnecessary processing such as filtering is not applied) and is
10 stored in the image memory 223 by the selector 220. Connectivity is calculated by the correction-value calculation circuit 224 from the stored image data. Here tone patches are cut from the image data and it is determined which of several patches have a density level
15 equivalent to highlight density. Connectivity parameters are calculated from the densities of these patches.

Correction when a connection is made through a network will be described next.

20 First, the network interface 212 establishes communication with a printer at the printing destination. This printer uses its CPU to extract connectivity parameters from the connectivity-parameter back-up RAM and sends this information to this side (the
25 sending side) via network communication means. The CPU 210 stores the sent connectivity parameters in the back-

now be described with reference to the drawings.

The fourth embodiment adds a memory 225, in which a number of connectivity parameters are stored in advance, to the arrangement of the third embodiment illustrated
5 in Fig. 23.

Fig. 24 is a block diagram illustrating the construction of an image processing section according to the fourth embodiment. As shown in Fig. 24, all connectivity parameters of a number of printers
10 connected to a network can be stored beforehand in the memory 225 instead of receiving connectivity parameters from another party when an output is to be produced.

The fourth embodiment is capable of dealing with a case where an output is made to a printer that does not
15 have a reader or that cannot calculate connectivity parameters on its own. In such cases it is necessary to correct connectivity parameters through the network.

The pattern generator 222 generates a test-pattern signal. This signal is input as an image signal by the
20 selector 221 and enters the network interface 212. The latter sends this binary pattern data to the printer on at the destination (on the receiving side), which proceeds to print out the pattern data. The sheet of paper on which the pattern data has been printed is read
25 by the reader of the printing apparatus on this side (the sending side). That is, the paper ejected from the

binarization circuit can be changed, a change in dot reproducibility caused by a change in environment or a change with time is read by a reader, the connectivity parameters are optimized for dealing with this change in dot reproducibility and a correction is carried out for each printer. This makes possible the stable reproduction of dots, even in a case where printing is performed over a network, at printers having different dot reproducibilities caused by a change in process conditions due to environmental change or by disparities in engine characteristics. Printing quality can be improved as a result.

According to the third and fourth embodiments, changes in the environment and change with time are dealt with by printing a test-pattern signal, reading the printout and changing the connectivity parameters. However, sensors for sensing temperature and humidity or a sensor for sensing drum film thickness may be provided and the connectivity parameters can be changed in conformity with outputs from these sensors.

The present invention can be applied to a system constituted by a plurality of devices (e.g., a host computer, interface, reader, printer, etc.) or to an apparatus comprising a single device (e.g., a copier or facsimile machine, etc.).

Furthermore, it goes without saying that the object

